

Wire-Free

W3 W6 WA

Wireless Headphone Kit



Deteknix Inc

1211 Center Court Dr. Suite 103 Covina, CA U.S.A. 91724

Tel: +1 (626) 559 7742 info@deteknix.com | www.deteknix.com

For more worldwide distributors information please visit our website.



Content

One lite headphone, one adopter , one USB 2.0 charger cable, one magnetic charger cable, two elastic bands, two iron pieces, one carry bag

Congratulations on your purchase of this Wire-Free wireless head- phones kit. Before using your headphones for the first time, please take a moment to carefully read the following information.

Safety Instructions

- When wear the headphones, make sure the volume is turned to mini- mum. Only adjust the volume after putting the headphones on. Do not turn the volume up too loud. You could cause permanent damage to your hearing.
- **Danger to life!** Headphones dramatically reduce your ability to hear ambient noise. Using headphones while in road traffic is potentially very dangerous and is therefore prohibited by law. Also, please make sure that you do not use your headphones when in the vicinity of possibly dangerous machines and tools.

Headphone Adjustment

Before wearing the Wire-Free lite headphone for the first time you should adjust it properly to achieve the best sound and ambient noise attenuation.



Unfold the headphone pad as the figure 1. and 2. Select the appropriate lock-in position on both sides of the headband as figure 3. The pads will adjust the angle automatically according to your head size.

Power on transmitter

Make sure the transmitter is fully charged and press the power button for 1 second. The LED indicator will start to flashing.

Power on headphone

Make sure the transmitter is fully charged and press the power button(between two volume button) for 1 second. The LED indicator will start to flashing.

Pairing transmitter with headphone

Place the headphone close to the transmitter in less than 10CM, press and release the power button of headphone quickly. The LED indicator of transmitter will turns to steady condition.

Power on transmitter

Make sure the transmitter is fully charged and press the power button for 1 second. The LED indicator will start to flashing.

Attach transmitter to your detector

We provide two methods to attach the transmitter to your detectors. For headphone jack on control box, you can clip it on the rod by elastic band. For headphone jack under the arm-rest, you can paste the iron piece on flat place and attach the transmitter on it.



Now you have turned your detector into wireless!

Transmitter recharging

You can recharge it thru laptop computer USB port, smartphone charger or power bank.

Plug the USB side into the port and place the magnet head on the transmitter's charging place.

The LED indicator will start to flashing. It will turns off when fully charged.



Headphone recharging

You can also charge the headphone thru the USB 2.0 cable by computer, smartphone charger or portable power bank.